






Remote control functions

button	Function
	When in static mode(default): to adjust the brightness(16 grades) When in jump3 , jump7 ,fade3, fade7 mode to adjust the light flashing rate(8 grades) When in music mode: to adjust the sensitivity of receiving music
On/Off	Turn on /off the controller
Red/green/blue White/orange Yellow/cyan/purple	To select corresponding static color
Jump3	3 colors jump changing
Jump7	7 colors jump changing
Fade3	3 colors gradual changing
Fade7	7 colors gradual changing
	Sound-control mode_I (general music), all colors will gradual or jump change following the music/ sound rhythm. If no music/sound input or sensed, all colors will gradual change.
	Sound-control mode_II (tenderness music), all colors will slow breathing or jump change following the music/sound rhythm. If no music/sound input or sensed, all colors will slow breathing change.
	Sound-control mode_III(active music), all colors will jump change following the music/sound rhythm. If no music/sound input or sensed, current colors keep lighting.
	Sound-control mode_IV(DJ music), all colors will jump following the music/sound rhythm. If no music/sound input or sensed, all colors are off.

Direction for use

1. Connect the load lines and power lines, make sure all connection correct before power switched on.
2. Insure there is no obstacle between the IR controller and the receiver when operating.
3. This product should not be used in outdoor and any other humid environment. Not allow to touch water or any liquid. No impacting and knocking. Should be not use in high temperature and high pressure environment to avoid the product damage and cause short-circuit, fire disaster and electric shock etc.
4. The manufacturers will not be responsible for the product damage, property damage, personal injury and any other losses which are caused by improper use.

Features:

20Key infrared Music LED controller adopts the advanced micro control unit. It is used for controlling a variety of LED lamp. For instance, point-source light, flexible strip light, wall washer light, glass curtain wall light and so on; it has many advantages such as low cost, convenient connection and ease of use. Meanwhile you could adjust brightness, static colors and color changing effects via infrared remote control. When it is in sound-control mode, the colors will change with the music rhythm.

Specifications:

Working temperature: $-20^{\circ}\text{C} \sim 60^{\circ}\text{C}$

Input voltage: DC12-24V

Output: 3 channels

Connecting mode: Common anode

External dimension: L63*W35*H22mm

Packing size: L215*W115*H25mm

Net weight: 50g

Gross weight: 66g

Static power consumption: $<1\text{ W}$

Output current: $<2\text{A}$ (each channel)

Output power: $<72\text{W}$